



Vendor: Red Hat

Exam Code: EX200

Exam Name: Red Hat Certified System Administrator (RHCSA)

Version: Demo

Exam Times:

RHCSA: Two and a half hours.

Pass Scores:

Total 300 points. Pass at 210 points.

Exam Environment:

Take examinations on a real system with a pre-installed virtual machine.

All exams must be completed in the virtual machine.

Network must be well configured. If the network cannot be accessed, you will not pass the exam.

In the iptables configuration, if you need to refuse the access, please use "Reject". (The default is set as ACCEPT.)

Note:

All the CD-ROM package has in `http://ip/dir/cdom` under.

You can use the real machine to verify that the exam experiment in the virtual machine is properly completed.

domain40.example.com domain 172.24.40.0/24 network.

tracker.com domain 172.16.0.0/16 network, general network rejected the meaning of the questions asked.

Boot the first thing

iptables-F

iptables-X

iptables-Z

service iptables save

QUESTION 1

Configure your Host Name, IP Address, Gateway and DNS.

Host name: station.domain40.example.com

IP Address:172.24.40.40/24

Gateway172.24.40.1

DNS:172.24.40.1

Correct Answer:

LANG= system-config-network-tui

(Config ip address, subnet mask, gateway, DNS, host name, the default search domain.)

/etc/init.d/NetworkManager restart

vim /etc/hosts

172.24.40.40 station.domain40.example.com

View Configuration:

cat /etc/sysconfig/network-scripts/ifcfg-eth0

IPADDR=172.24.40.40

GATEWAY=172.24.40.1

DNS1=172.24.40.1

cat /etc/resolv.conf

search domain40.example.com

nameserver 172.24.40.1

cat /etc/sysconfig/network

HOSTNAME=station.domain40.example.com

cat /etc/hosts

172.24.40.40 station.domain40.example.com

OR

Graphical Interfaces:

System->Preference->Network Connections **(Configure IP Address, Gateway and DNS)**

Vim /etc/sysconfig/network **(Configure Host Name)**

QUESTION 2

Add 3 users: harry, natasha, tom.

The requirements:

The Additional group of the two users: harry, Natasha is the admin group.

The user: tom's login shell should be non-interactive.

Three user password set uplooking.

Correct Answer:

```
# groupadd admin
# useradd -G admin harry
# useradd -G admin natasha
# useradd -s /sbin/nologin tom
# echo uplooking | passwd --stdin harry
# echo uplooking | passwd --stdin natasha
# echo uplooking | passwd --stdin tom
# id harry;id Natasha (Show additional group)
# cat /etc/passwd (Show the login shell)
```

OR

```
# system-config-users
```

QUESTION 3

Create a catalog under /home named admins. Its respective group is requested to be the admin group. The group users could read and write, while other users are not allowed to access it. The files created by users from the same group should also be the admin group.

Correct Answer:

```
# cd /home/
# mkdir admins /
# chown .admin admins/
# chmod 770 admins/
# chmod g+s admins/
```

QUESTION 4

Configure a task: plan to run echo hello command at 14:23 every day.

Correct Answer:

```
# which echo
# crontab -e
23 14 * * * /bin/echo hello >> /tmp/hello.log
# crontab -l (Verify)
```

QUESTION 5

Find the files owned by harry, and copy it to catalog: /opt/dir

Correct Answer:

```
# cd /opt/
# mkdir dir
# find / -user harry -exec cp -rfp {} /opt/dir/ \;
(-rf Forced recursive, -p copies permissions)
```

EnsurePass.com Members Features:

1. Verified Answers researched by industry experts.
2. Q&As are downloadable in PDF and VCE format.
3. 98% success Guarantee and **Money Back** Guarantee.
4. Free updates for **180** Days.
5. **Instant Access to download the Items**

View list of All Exam provided:

<http://www.ensurepass.com/certifications?index=A>

To purchase Lifetime Full Access Membership click here:

<http://www.ensurepass.com/user/register>

Valid Discount Code for 2015: JREH-G1A8-XHC6

To purchase the HOT Exams:

| <u>Cisco</u> | | <u>CompTIA</u> | | <u>Oracle</u> | <u>VMWare</u> | <u>IBM</u> |
|--------------------------------|--------------------------------|--------------------------------|--------------------------------|--------------------------------|----------------------------------|----------------------------------|
| <u>100-101</u> | <u>640-554</u> | <u>220-801</u> | <u>LX0-101</u> | <u>1Z0-051</u> | <u>VCAD510</u> | <u>C2170-011</u> |
| <u>200-120</u> | <u>200-101</u> | <u>220-802</u> | <u>N10-005</u> | <u>1Z0-052</u> | <u>VCP510</u> | <u>C2180-319</u> |
| <u>300-206</u> | <u>640-911</u> | <u>BR0-002</u> | <u>SG0-001</u> | <u>1Z0-053</u> | <u>VCP550</u> | <u>C4030-670</u> |
| <u>300-207</u> | <u>640-916</u> | <u>CAS-001</u> | <u>SG1-001</u> | <u>1Z0-060</u> | <u>VCAC510</u> | <u>C4040-221</u> |
| <u>300-208</u> | <u>640-864</u> | <u>CLO-001</u> | <u>SK0-003</u> | <u>1Z0-474</u> | <u>VCP5-DCV</u> | <u>RedHat</u> |
| <u>350-018</u> | <u>642-467</u> | <u>ISS-001</u> | <u>SY0-301</u> | <u>1Z0-482</u> | <u>VCP510PSE</u> | <u>EX200</u> |
| <u>352-001</u> | <u>642-813</u> | <u>JK0-010</u> | <u>SY0-401</u> | <u>1Z0-485</u> | | <u>EX300</u> |
| <u>400-101</u> | <u>642-832</u> | <u>JK0-801</u> | <u>PK0-003</u> | <u>1Z0-580</u> | | |
| <u>640-461</u> | <u>642-902</u> | | | <u>1Z0-820</u> | | |

